



# COMPACTRONS


TYPE	DESCRIPTION	CHARACTERISTICS SIMILAR TO	BASING
1AD2	HV Diode	1J3 HV Rect.	12DQ
2AH2	HV Diode	3A3 HV Rect.	12DG
2AS2	HV Diode	2AH2 HV Rect.	12EW
3AT2	HV Diode	3A3 HV Rect.	12EX
4HA7	Dissimilar	12AU7 (Pins 4, 9, 10) plus 12AX7	12FQ
6AF11	Double Triode	Hi-Mu Tri.	12DP
6AG11	Dbl.-Tri. Pent.	(Pins 5, 6, 8) plus 6CX8	12DA
6AL11	Duplex-Diode	12AT7 Twin Tri. plus 6BW8 Di. with Sep. Cath.	12DA
6AR11	Twin Triode	6DT6 (Pins 2, 3, 4, 6, 7) plus 6AQ5	12BU
6AS11	Dissimilar	Two 6GM6 Pent.	12DM
6AV11	Dbl.-Tri. Pent.	Hi-Mu Tri. (Pins 5, 6, 8) plus 6CX8	12DP
6AX3	Triple Triode	Three 12AU7 Tri.	12BY
6AY11	Diode	6AX4-GTB Damp. Di.	12BL
6B10	Duplex-Diode	12AX7 Twin Tri.-plus 6BW8 Di. with Sep. Cath.	12DA
6BA11	Twin Triode	12AU7 Twin Triode	12BF
6BD11	Duplex-Diode	plus 6W8 Diode	12BF
6BE3	Diode	6H58 plus Medium Mu Tri.	12ER
6BF11	Tri-Twn. Pent.	Med. Mu Tri. (Pins 3, 4, 7), High-Mu Tri. (Pins 5, 6, 8), plus Video Pent.	12DP
6BH11	Dbl.-Tri. Pent.	Damper—Max. Ratings: PIV=5000V. DC Output =200 ma.	12BL
6BJ3	Diode	6DT6 (Pins 2, 3, 5, 6, 7) plus Power Output Pent.	12EZ
6C10	Double Pentode	Two 6G8 Triodes	12FP
6D10	Twin-Triode	plus 6GH8 Pent.	12FP
6EJ7	Pentode	6W4-GT Damper	12BL
6FM7	Diode	Three 12AX7 Triodes	12BQ
6FY7	Triple Triode	12AT7 Triodes	12BY
6G11	Dissimilar	6DN7 Vert. Osc. (Pins 9, 10, 11) and Amp.	12BM
6GE5	Double Triode	6EA7 Vert. Osc. (Pins 9, 10, 11) and Amp.	12EJ
6GF5	Dissimilar	6DR7 Vert. Osc. (Pins 9, 10, 11) and Amp.	12EO
6GV5	Double Triode	6DT6 (Pins 2, 3, 4, 6, 7) plus 6CU5	12BU
6GY5	Dissimilar	6DQ6-B Hor. Defl. Amp.	12BJ
6HB5	Beam Pentode	6DQ6-B Hor. Defl. Amp.	12BJ
6HD5	Beam Pentode	6DQ6-B Hor. Defl. Amp. Hor. Defl. Amp.—Max. Ratings: Plate Dis.=18 W, DC Cath. Cur.=230 ma.	12DR
6HE5	Beam Pentode	6GY5 Hor. Defl. Amp.	12BJ
6HF5	Beam Pentode	Hor. Defl. Amp.—Max. Ratings: Plate Dis.=24 W, DC Cath. Cur.= 280 ma.	12ES
6J10	Beam Pentode	6E25 Vert. Defl. Amp.	12EY
6J11	Beam Pentode	6DQ5 Hor. Defl. Amp.	12FB
6JZ8	Pentode-Gated Beam Disc.	6BN6 plus 6AL11 Power Out. Pent.	12BT
6K11	Twin Pentode	Two 6EW6 Pent.	12BW
6M11	Triode-Pentode	6SN7 Tri. plus 12R5 Pent.	12DZ
6Q11	Three Section Triode	One 12AU7 (Pins 4, 9, 10) plus two 12AX7	12BY
6T9	Twin-Triode	Two 12AT7 plus 6EW6 Pent.	12CA
6U10	Pentode	6K11	12BY
8B10	Three Sect. Tri. Triode-Pentode	6AL11 Power Pent. plus one 12AX7	12FM
10AL11	Dis. Dbl. Pent.	6AL11	12EZ
11AR11	Three Section Triode	One 12AX7 (Pins 5, 6, 7) plus two 12AU7	12FE
12AL11	Duplex-Diode	6B10	12BF
12AX3	Twin Triode	6AL11	12BU
12BE3	Dis. Dbl. Pent.	6AR11	12DM
12B3	Diode	6AL11	12BU
12B7	Diode	6AX3	12BL
12GE5	Diode	6BE3	12BL
12J10	Diode	6W4-GTA	12BL
15AF11	Beam Pentode	6GE5	12BJ
15BD11	Pentode-Gated- Beam Disc.	6J10	12BT
15FM7	Dis. Dbl. Tri.	6AF11	12DP
15FY7	Dbl.-Tri. Pent.	6BD11	12DP
16GY5	Dis. Dbl. Tri.	6FM7	12EJ
17AX3	Dis. Dbl. Tri.	6FY7	12EO
17BE3	Beam Pentode	6GY5	12DR
17BF11	Diode	6AX3	12BL
17GE5	Diode	6BE3	12BL
17GV5	Dis. Dbl. Pent.	6BF11	12EZ
17JZ8	Beam Pentode	6GE5	12BJ
21GY5	Beam Pentode	6GV5	12DR
21HB5-A	Beam Pentode	6JZ8	12DZ
21HJ5	Beam Pentode	6GY5	12DR
22B3	Beam Pentode	6HB5	12BJ
22BV3	Beam Pentode	6HB5	12BJ
23Z9	Beam Pentode	6DQ5 with Ext. Conn. to Suppressor	12FL
30AG11	Diode	22DE4	12BL
33G17	Dis. Dbl.-Tri. Pent.	6JZ8 plus Med.-Mu Tri. (Pins 7, 10, 11)	12FT
33GY7	Duplex-Diode	6AG11	12DA
38E7	Twin-Triode	6GE5 plus 6AX3	12FC
7984	Diode-Pentode	6GE5 plus 6AX3	12FN
8156	Diode-Pentode	6HB5 plus 6BJ3	12FS
	Beam Pentode	6146	12EU
	Beam Pentode	R-F Power Amp.—21 W Output (IMS) at 175 Mc	12EU




12BF  
6B10, 8B10




12BJ  
6GE5, 6GF5, 6HB5,  
12GE5, 17GE5, 21HB5,  
21HB5A




12BL  
6AX3, 6BE3, 6BJ3,  
12AX3, 12BE3, 12BT3,  
17AX3, 17BE3, 22BW3




12BM  
6FJ7




12BQ  
6C10




12BT  
6J10, 13J10




12BU  
6AL11, 6G11,  
10AL11, 12AL11




12BW  
6J11




12BY  
6AV11, 6D10,  
6K11, 6Q11




12CA  
6M11




12DA  
6AG11, 6AY11, 30AG11




12DQ  
2AH2




12DM  
6AR11, 11AR11




12DP  
6AF11, 6AS11, 6BD11,  
15AF11, 15BD11




12DQ  
1AD2




12DR  
6GV5, 6GY5, 16GY5,  
17GV5, 21GY5




12DZ  
6JZ8, 17JZ8




12EJ  
6FM7, 15FM7




12EO  
6FY7, 15FY7




12ER  
6BA11




12ES  
6HD5




12EU  
7984, 8156




12EW  
2AS2




12EX  
3AT2




12EY  
6HE5




12EZ  
6BF11, 6T10, 17BF11




12FB  
6HF5




12FC  
33GT7




12FE  
6U10




12FL  
21HJ5




12FM  
6T9




12FN  
33GY7




12FP  
6BH11



12FQ  
4HA7



12FS  
38HE7



12FT  
23Z9